# **Vulca Voice**

# **Voice Alarm System** All-in-one system

Pready

EN 54 - 16



## **Key points**

- **(** Compact system, all-in-one wall box
- **(** From 1 to 4 loudspeaker lines
- **(**9 Integrated amplifiers: up to 400W

USB port / 2 AUX inputs

**Import Export** & configurations Music broadcasting





Integrated emergency microphone Flexible wired microphone

Integrated power supply and batteries


Space saving

### More details

Vulca Voice is a range of compact EN54certified Voice Alarm Control and Indicating Equipment.

Integrated SD memory card associated with digital player makes it possible to easily customize your messages and create different programs. Thanks to its IP communication protocol, it can directly communicate with a network controler such as a distant IP console. Implementation is optimized thanks to full equipment integration (amplifiers, power supply and batteries) and adapted interfaces.

FEATURES			
Inputs	6 (USB / XLR / RCA / RJ45 / Phone terminal / SD card (integrated))		
Outputs	1 to 4 100V – 300W max per output		
Frequency range	50 – 20 000 Hz		
THD + N	< 1%		
S/N ratio	> 70 dB		
Interfaces	Ethernet IP USB		
Power supply	230V AC / 920VA max Batteries 2 x 12V - 38Ah		
Dimensions	520x530x240mm		
Material	Metal		
Color	Grey		
Weight	Without batteries : 20,5 kg With batteries <sup>(1)</sup> : 38,5 kg		





# **Vulca Voice**

# Voice Alarm System All-in-one system

# Range

Reference	Without backup amplifier		With backup amplifier	
	Number of	Total power	Number of	Total power
	zones		zones	
CSC1-310	1	300 W	NA	NA
CSC1-420	2	400 W	1	300 W + 300 W
CSC1-430	3	400 W	2	400 W + 300 W
CSC1-440	4	400 W	3	400 W + 300 W

# System example

