


PGM-1000

Microphones Microphone console

Key points

- 1 zone paging console
- Removable XLR gooseneck
- Phantom power supply or AA batteries
- XLR cable supplied



39cm max. flexible
Removable gooseneck



Cardioid microphone cell
Ideal for voice announcements

1 zone selection luminous button
Easy to use

More information

PGM-1000 microphone console is of cardioid type (picks up sounds mainly coming from the front).

It is ideal to broadcast voice announcements in an area thanks to its single luminous button.

It is easy to connect with its male XLR output (an 8 meter XLR cable with 6.35mm jack adapter is included with the product).

It can be powered with 2 x AA batteries or directly through another device that supply phantom power.

FEATURES

Directivity	Cardioid
Impedance	200Ω
Sensitivity	- 40dB
Frequency response	20 Hz – 20 kHz
Flexible	39cm / XLR female
Connectors	Male XLR output
Power	78V phantom or AA batteries (LR6)
Dimensions (base)	16 x 11,4 x 5,7cm
Color	Black
Material	Plastic
Weight	700g
Others	8 meters XLR cable + Jack 6.35mm adapter + mic. protective sponge

